

NOTE: Wire dimming conductors as Class 1

1 SINGLE FIXTURE

Locate ceiling mounting points according to supplied client drawing. Make a knot in the power cord (A) and then connect it to the ceiling power feed.

2 POWER SIDE

Secure canopy (B) with slip ring (C) on threaded rod (D).

3 NON-POWER SIDE

Secure canopy (E) with cable coupler (F) on threaded rod (G) (by other).

4

Insert the aircraft cable (H) into the griplock (I). Adjust the cable (H) length by pushing the feeder tube (J) and **cut the excess cable** with an aircraft cable cutter (K).

5

Secure power cord (A) to aircraft cable (H) with plastic clip (L).

6 CONTINUOUS SYSTEM

POWER SIDE **NON POWER SIDE**

For a continuous system, repeat steps 1 to 3 for all fixtures in the run.





